

Art No. PA0031

Universal Power Adapter for Netbook 40W

Freature:

- Charge your notebook
- Compact 40 Watt Universal Netbook power adapter
- Switchable 9.5V/10.5V/12V/14V/15V/16V/18.5V/19V DC notebook power output
- Universal, can be used for all notebook up to 40 Watt
- Protected against overload, short circuit and overheating
- With 8 power tips to suit to most of Laptops
- Casing Dimension: 93.3 (H) x 37 (L) x 25.5 (W) mm

Specification:

1.	Rated Input Voltage (50-60Hz)	AC120V or AC230V
	Vibration Input Voltage Range (47-63Hz)	AC110V-240V
2.	Input Rated Current	0.9Amp
	Input Power	90VA
3.	Output power (max)	40W
	Efficiency	>80%(TYP)
4.	Output voltage: 9.5/10.5/12/14/15/16/18.5V/19V	DC9.5V-19V
	(0±0.8V No Load)	
5.	Output voltage:	
	9.5/10.5/12/14/15/16/18.5V/19V (-0.6±0.6V@rating	DC9.5V-19V
	load)	2AMP(max)
	Output current:	, ,
	9.5/10.5/12/14/15/16/18.5V/19V@2 Amp Max	
6.	Overload protection	YES
7	Short Circuit Protection	YES
8.	Line Regulation	±5%
9.	Load Regulation	±5%














Art No. PA0031

Universal Power Adapter for Netbook 40W

Compatible power tips list:

Tips No.	Dimension of Tips	Brand
Α	6 x 4 x 1	-
В	6.3 x 3	-
С	5.5 x 2.5	Dell, Fujitsu Siemens, MSI, LG, Lenovo, Advnet, Medion
Е	5.5 x 1.7	Acer
F	4.8 x 1.7	ASUS, SONY
G	4.0 x 1.7	HP
Н	5 x 3.4 x 1	Samsung
Τ	2.5 x 0.7	ASUS

Package Content:

- 1 x 40Watt Universal Power Adapter
- 8 x Compatible Charge Source Power Tips
- 1 x User Manual
- 1 x Carrying Bag

Packaging Information:

• Packing Dimension: 154x203x70mm

Packing Weight: 0.345 kg

• Carton Dimension: 475x330x215 mm

• Carton Q'ty: 20pcs • Carton Weight: 7.7kgs







RoHS

EFFICIENCY LEVEL: (V)



